


## 13A Socket Adaptor Receiver

For Wireless Kinetic Switches

SKU No. : WS1080 Model No. : ECO-P01



**User Manual**

### Parameter

Power Supply	AC100~240V, 50/60Hz
Control Load	13A
Maximum Power	3500W INC (240V) 2000W LED (240V)
Pairing Capacity	Maximum 6 switches
Operating Range	20m
Colour	White
Weight	124g
Certifications	CE/RoHs/FCC/UKCA
Plug Type	UK
Dimensions	L110mm*W62mm*H56mm

### Instructions

**1. Pairing Method:** Press the "Pairing button" for 3 seconds, the plug will enter the pairing mode. After the red light indicator is constantly on, press the kinetic switch once.

Note: If paired successfully the red light indicator will flash once. If no action with the plug, then the plug will exit the pairing mode after 60 seconds.

**2. Directional Pairing Method:** Only fit for 2-Gang and 3-Gang switch. Press the "Pairing button" for 3 seconds, the plug will enter the pairing mode. After the red light indicator is always on, press the kinetic switch 3 times within 15 seconds.

Note: If no action with the plug, then it will exit the pairing mode after 60 seconds.

**3. Clear Pairing:** Press the "Pairing button" for 7 seconds. The red light indicator will flash 3 times and all paired devices will get cleared. This will clear the directional mode to default.

### Frequently Asked Questions

1. How many switches can be paired with a smart plug?  
Up to 6.

2. Can it connect to Wi-Fi or bluetooth ?  
No.

3. The Rate power is 13A, but why did the plug burn out when I use it on my 3000W motor?

Because the instantaneous current of motor is very large, far over 13A. Maximum 2000W is recommend for motor power pairing.

### Stuck? Confused?

Contact our Technical Support team on:

T: +44 (0)1291446105 | E: support@ener-j.co.uk

Lines are open Mon - Fri (8am to 4pm)