

**Product Parameters:**

Material: Zinc Alloy/ ABS  
Overall Size :145\*105\*55mm  
Working Voltage :4.5-6 V  
Working Temperature :-20°C~60°C

Power Interface: Micro USB  
Internal Size :112\*80\*28mm  
Battery Life :12+ months  
Waterproof Rating: IPx5

**Accessories:**

Key Box	--1 Piece	User Manual	--1 Piece
Drill Template	--1 Piece	USB Cable	--1 Piece
Bolts	--4 Pieces	Screws	--4 Pieces

**Installation :**

- 1) Mark 4 positioning points on the wall or door with the drilling template.
- 2) Use electric drill to punch holes in marking positions (Ø6 x30 mm), then insert the plastic bolts.
- 3) Open the front lid and fix it with the screws in the installation bag.

**Notes:**

- 1) The 4 AAA alkaline batteries are not included. Please use Micro USB cable to connect the charging port then enter 123456 and to insert the batteries, press the OK button to open the front cover.
- 2) After the lock box is configured,the initial password 123456 will be invalid and needs to be modified in the password settings.
- 3) It needs network connection to set password,view record,remove device.
- 4) Once the box is binded, only need to enable Bluetooth to unlock.
- 5) The family members are the administrators,with all permissions to set and modify passwords, share devices, view records, etc.

Other group members who join through invitations are regular users who can only access the group using a mobile device or passwords shared by the administrator.

**FCC, CE, RoHS Certificates**

**Stuck? Confused?**

Contact our Technical Support team on:  
T: +44 129 144 6105 | E: support@ener-j.co.uk  
Lines are open Mon - Fri (8am to 4pm)

**Imported and Marketed By:**  
ENERJ SMART LTD.  
Unit 11D Cosgrove Way, Luton LU11XL,  
United Kingdom

**ENER-J®**

Smart Home Living

# Smart Lock Box User Manual



SKU: SHA5333

Model No: SMKB2-BT

**User manual**

**Download APP:**

Searching "EnerjSmart" on stores to download and install the APP.



**Create Account:**

Follow instructions in app to create an account with user's mobile phone number.

**Install Battery:**

Use the Micro USB cable to connect the charging port, then enter the initial passwords 123456+ to insert the batteries, press the OK button to open the front cover.

**Add Device:**

- Register the "EnerjSmart" account and log in (Need network);
- "Add Device" or click the symbol "+" in "Home" page;
- Select "Auto Scan" to start searching device;
- Click "Next" to add the key box.

**Family Management:**

- Login APP-- Select the device and enter the "Family" page;
- Tap the first user(Administrator) to set several permanent passwords;
- Tap the "+" to add members;
- Enter the user's name and account to set the family role.
- Common Member / Administrator

**Temporary password types:**

- ◆ Time-limited password: (Use at least once within 24 hours after it takes effect)
- ◆ One-time password: (Only one time to unlock and valid for 6 hours)
- ◆ Dynamic password: ( Multiple times to unlock and valid for 5-10 minutes)
- ◆ Clearing password: ( The selected password or all the time-limited one that has been used would be deleted. It is valid for 24 hours)
- ◆ Custom password: (The device must connect to user's phone thru bluetooth)

**Temporary Passwords Management:**

- Password sharing settings: (The receiver must have their app account)
- Login APP-- Select the device and enter the "Temporary" page;
- Select password type;
- Set the Effective and Expiration time;
- Obtain the passwords then copy and share with others .

**Mobile phone password settings:**

- Login APP-- Select device and enter the "Temporary" page;
- Select password type under mobile phone option;
- Enter the receiver's mobile phone or email address;
- The receiver login the app and unlock the device.

**APP Unlock:**

- Rapid unlock:
- Login APP-- Enter the device page- Long press the unlock icon.

**Password Unlock:**

- Enter the passwords;
- Press OK button on the device keypad.

**View Access Logs:**

- Login APP--Enter the device page--Click unlocking records.

**Remove Device:**

- Press the device icon on the home page for 3 seconds;
- Click [ Remove device] to delete.

**Share Device:**

- Login APP--Enter the device page;
- Click the symbol on the upper right corner;
- Share device.

**More Settings:**

By using these features in the smart scenes, the user will have a better experience. Please edit the scenes according to the instructions.