ENER-J®
Smart Home Living

WI-FI WATERPROOF
TWIN SOCKET IP66

User Manual

---

1 Installation

Parameter

Model	SHA5274
Rated Voltage	90V-250V AC
Max Current	13A Gang
Wireless Standard	WI-FI 2.4Ghz
Material	PC

1. Install ENERSMART app into smart phone or tablet device. Or scan the QR code, download and install into smart phone or tablet device. Also works with Amazon Alexa & Google Home.

Download Our App

ENERJSMART
To download,
Scan the QR code

Android

iOS

Google Home

WORKS WITH
amazon alexa

2. Power up: On/Off operating principle. The connected appliances work/stop through live wire power on/off.
3. Cut off the power. Use screw driver to open the rear cover. Connect the wires correctly. Install and power it up.

1. **Reset function
   (Hold for 10 seconds).**
2. **USB Port.**

---

4. Set up: Press and hold any button(switch) for 10 seconds till the LED Indicator flashes rapidly.

Choose your device

SMART LIFE

No Device

ADD DEVICES

Experience Center

SELECT DEVICE TYPE

Scan new devices via Bluetooth   Scanning

Electrical outlet

Multiple socket

Wall switch

Lighting devices

Lighting devices (bluetooth-enabled)

Air conditioner

Robot vacuum

Cancel

Enter Wi-Fi Password

Wi-Fi:SmartSocket   Change Network

Confirm

This app is supported only on 2.4GHz Wi-Fi channels

Input your WI-FI SSID and password

ADD DEVICE

Succesfully Added 1 Device(s)

wifi device

Share with Family

Done

When the green light keeps on, the device is online. Start to control now!

---

2 Installation Diagram

1 Products and accessories display	2 Use a screwdriver to pry the panel
3 As is shown in	4 Noted — 8mm — Cut the wire around 8mm
5 Connect the wire to the appropriate location	6 Tighten the two screws, the installation is complete