





SKU Code: SHA5220 EAN Code: 7103353842129

Wireless Video Door Bell with 16GB TF Card, night vision and 2 way Audio





Download Our App



ENERJBELL 2

How to install



Download our free to use APP ENER] BELL 2 from your Android Playstore or iOS Store, add the Doorbell by scanning the bar code on the back of the unit, connect with your home Wi-Fi and you are ready to enjoy!

Product Features

- · HD720P image ultra-Low Power Consumption Design
- Quick access via app (automatically wakes up within 3 seconds)
- · Respond to user's access demands within 1 second
- 6pcs IR LEDs, D/N mode auto switch by Light Sensor
- APP support iOS & Android, Support 2-way audio with noise cancellation
- Automatic take a picture & video recording when visitor press doorbell
- · Anti-Tamper Alarm Function
- · PIR Motion Detect Alarm
- · Cloud Storage Function
- Support max 32GB SD TF card (save video recording)
- Built-in Lithium Battery and Easy Charged by USB
- The Newest Design Case-Weatherproof
- Easy Installation (no need any cable), just Wi-Fi connection

Specification	
Solution	OV9712 CMOS Sensor + Hi3518E SoC
Display Resolution	1.0MP-1280x720P
Focal Length	1.7mm, 166° Wide angle
Input/Output	Built-in microphone&speaker
Audio Type	2-way audio with noice cancellation
Video Compression	H.264
Video Resolution	1280 * 720@25fps
Night Visibility	6pcs IR-LEDS
D/n Mode	Auto switch by Light Sensor
PIR Motion Detect	Yes
Anti Tamper Function	Yes
Protocol	TCP/IP, UDP, DHCP, P2P, RTSP, FTP
Wireless Standard	2.4GHz Wifi IEEE 802.11b/g/n
Mobile phone memory	Yes
SD TF Card	Up to 32GB Max.(video recording)
Cloud Function	Yes
Dimension	125(L)*67(W)*23 (H) mm
Color box	163(L)*103(W)*56 (H) mm
Net Weight	150g
Gross Weight	350g
Shell Material	Aluminium Alloy
Power Supply	3000mHA battery, charged by USB
Working mode	Average power consumption: 170mA
Stand by mode	200uA
User Accounts	Total 4 Users (Admin user and normal user)
Working temperature	-20°C to 55°C
-	

www.ener-j.co.uk info@ener-j.co.uk