

Outdoor Socket with Timer, Compatible with Alexa Echo Google Home Remote Control Lighting.



British standard double hole, independent sub-control







1 USB Ports Total of 2.1Amp.5VDC

Receptacle 13 Amp 250VAC 60Hz











Features

- Outdoor hardwired smart plug-in socket which can also be voice controlled via echo dot or google home.
- IP55 waterproof designed Smart wifi Socket which can withstand damp and wet conditions. Being made with a sealing lid cover makes it perfect for for bathrooms, patio light and outdoor string LED lighting or fountains.
- Wireless remote control the connected device on/off from your smartphone via our Free to Download and Use App ENERJSMART from anywhere as long as you have internet connection. Only works with 2.4GHz WIFI, 5G wifi is not supported.
- You can set scheduled timer to automatically power on/ off connected device, perfect for decorative or seasonal lighting, landscape lighting, garden fountains, pumps and other indoor and outdoor plug-in appliances.
- After wiring the device with mains, simply plug a device into the Smart Socket and connect to your Wi-Fi network. No hub required. No Monthly Fees.

| Specifications | |
|----------------------------|--------------------------------------|
| model no/SKU | Quve-362 / SHA5303 |
| Colour | Grey |
| Size | (L)170*(W)150*(H)80mm |
| Weight | 580g |
| Material | PC / ABS |
| Voltage range | 100-240V AC |
| Max current | 13A |
| Wireless frequency | 2.412~2.484GHz (5G not supported) |
| Wireless IEEE standards | IEEE802.11b/g/n |
| Wireless cunsumption | ≤0.3W |
| Working condition | Temp:-30~60°C |

www.ener-j.co.uk info@ener-j.co.uk